# Product Manual


## Intelligent Helmet Bluetooth Headset

V1.0

# Product Specifications

| Product | Parameter |
|---|---|
| Product Model | MAXRUNON D10 |
| Bluetooth Name | MAXRUNON D10 |
| Bluetooth Version | 5.4 |
| Speaker Unit | 40 mm |
| Boom Microphone | Bidirectional |
| Wired Microphone | Omnidirectional |
| Voice Noise Reduction | Yes, AI Noise Reduction |
| Battery Capacity | 1000mAh |
| Waterproof Level | IPX7 |
| Base | Back-Clip |
| Charging Port | Type-C |
| Group Intercom | 4 Riders |
| FM Function | Yes |
| Voice Command | Yes |
| Universal Pairing | Yes |
| Intercom Distance | Device Supports Bluetooth intercom, allowing up to 4 users to connect and communicate over 1-2 kilometers. |

• Device supports 18 offline voice commands.
• Do not use a high-pressure washer gun to wash the device
• Do not use a charger that exceeds 15V, and avoid charging the headphones when they are wet.





1. Volume -
2. Volume+
3. Function button
4. Intercom button
5. Audio Interface
6. Type-C Charging Port

## · PACKAGE CONTENTS



MAXRUNON D10 Main Unit




Speaker Unit




Velcro For Hybrid Mic



Microphone Sponge



3M Glue Plate



Back Clip




Manual




Wired Microphone



Boom Microphone



Type-C Cable



Velcro For Speaker



Speaker Pads



Velcro For Boom Mic


## · APP Download

For more features, please scan the QR code to download, install and use the APP.

## · Tech Support

support@maxrunon.com

# 1.Function




**Note:**
**The product appearance in the image is for reference only;**
**Please see the actual product.**

1. Volume -
2. Volume +
3. Funciton button
4. Intercom button
5. Audio Interface
6. Type-C Charging Port

# 2.Basic operations

There are two methods for operating your devices:voice commands and buttons. Select your preference.

- **Power on/off**

Button operation

4 + 3 2S

- **Phone pairing**

Voice operation

Hi Max, phone pairing

YOU CAN ALSO

Button operation

3 3S

- **Microphone on/off**

Button operation

4 + 2 2S

Note: Simultaneously long press the intercom button and any volume button for 2s.

- **Activate the intelligent voice assistant**

Voice operation

Hi Max

Note: “Voice Dialing” switch must be turned on in the app first.

- **Volume up**

Voice operation

Hi Max, volume up

YOU CAN ALSO

Button operation

2

- **Volume down**

Voice operation

Hi Max, volume down

YOU CAN ALSO

Button operation

1

- **Restoring factory settings**

Button operation

2 + 3 3S

Note: The device will reboot and reset to the manufacturer settings.

# 3.Music

- **Play music**

Voice operation

Hi Max, music on

YOU CAN ALSO

Button operation

3

- Pause music

Voice operation

Hi Max, pause music

YOU CAN ALSO

Button operation

3

Note: Ensure the music player is active

- Switch music

Voice operation

Hi Max, previous track

YOU CAN ALSO

Button operation

2 3S

Voice operation

Hi Max, next track

YOU CAN ALSO

Button operation

1 3S

## 4.Radio

**Please check the specification to see if this function is supported.**

- Turn on/off radio

Voice operation

Hi Max, radio on

Hi Max, turn off the radio

Button operation

3 ×2 Tap

## 5.Switch station

**Please check the specification to see if this function is supported.**

**Note: Radio function must be turned on.**

Voice operation

Hi Max, previous station

Hi Max, next station

YOU CAN ALSO

Button operation

To switch to the previous FM channel.

2 3S

To switch to the next FM channel.

1 3S

Note: In FM playback mode, short press 3 to go to the next station and play.

## 6.Phone call

- Answer phone call

Voice operation

Hi Max, answer the phone

YOU CAN ALSO

Button operation

Short press any Button to answer.

- End phone call

Voice operation

Hi Max, hang up

YOU CAN ALSO

Button operation

4

### • Reject phone call

Voice operation

Hi Max, hang up

YOU CAN ALSO

Button operation

4 3S

### • Automatic call answering function on/off

Button operation

Can be turned on and off by APP.

1 + 2 3s On/Off

## 7.Communicate with others

**This product has 2 modes:**
**Group Mode & Free Mode.**
Switching from group mode to universal pairing will disconnect the intercom from group mode and enter pairing mode.

### • Group mode

**Please refer to the product specification for the maximum paring members**

Group Mode is a private communication feature based on Bluetooth intercom technology. A group network must be set up before communication starts, and it supports up to 4 participants for group communication.

### • Group mesh

Voice operation

Hi Max, group mesh

YOU CAN ALSO

Button operation

4 2S

After hearing the number of team members on the broadcast

4

### • Group mode

Voice operation

Hi Max, group mode

YOU CAN ALSO

Button operation

4 Switch

### • Cancel group mesh

Button operation

Cancer the group when you're in the group mesh state.

4 2S

### • Free mode

**Please refer to the product specification for the maximum paring members**

Free mode is an open intercom mode that does not require pairing. As long as you are in the communication range, you can automatically connect up to 4 people for intercom.

Voice operation

Hi Max, free mode

YOU CAN ALSO

Button operation

4 Switch

### • End intercom

Voice operation

Hi Max, end intercom

YOU CAN ALSO

Button operation

4

- Bluetooth universal pairing

Button operation

With power on

3 3S

light flashes red and blue.

Voice announcement “Start pairing”
Simultaneously, other bluetooth headsets need to activate bluetooth pairing mode

4 ×2 Tap

light flashes red and green.

Voice announcement “Universal pairing”
Voice announcement“Universal connected”

3 ×2 Tap

Activate intercom

- Turn off Bluetooth universal pairing

Button operation

3 ×2 Tap

## 8.Quick operation

This product has two operation modes: intelligent voice and buttons, and you can freely choose according to your own habits.

- When the main unit is connected to the official app and the phone is connected to the internet, the main unit can perform intelligent voice interaction operations such as route navigation, sending messages, making and receiving calls, playing music, and so on.
- When not connected to the network, the main unit can perform voice commands through local offline voice commands.

Awakening words Hi Max

| Function | Voice command | Or | Button operation |
|---|---|---|---|
| POWER ON/OFF | | | 4 + 3 2S |
| PLAY MUSIC | Hi Max, music on | | 3 |
| PAUSE MUSIC | Hi Max, pause music | | 3 |
| PREVIOUS TRACK | Hi Max, previous track | | 2 3S |
| NEXT TRACK | Hi Max, next track | | 1 3S |
| VOLUME + | Hi Max, volume up | | 2 |
| VOLUME - | Hi Max, volume down | | 1 |
| ANSWER CALL | Hi Max, answer the phone | | Any button |
| END CALL | Hi Max, hang up | | 4 |
| REJECT CALL | Hi Max, hang up | | 4 3S |
| PHONE PAIRING | Hi Max, phone pairing | | 3 3S |
| GROUP MESH | Hi Max, group mesh | | 4 2S |
| | | ○ | After hearing the number of team members on the broadcast |
| | | ○ | 4 |
| GROUP MODE | Hi Max, group mode | | 4 |
| FREE MODE | Hi Max, free mode | | 4 |
| UNIVERSAL MODE | | ○ | 3 3S |
| | | ○ | Other bluetooth headsets need to activate bluetooth pairing mode |
| | | ○ | 4 ×2 Tap |
| | | ○ | 3 ×2 Tap |
| | | | Activate intercom |
| END INTERCOM | Hi Max, end intercom | | 4 |
| RADIO ON | Hi Max, radio on | | 3 ×2 Tap |
| RADIO OFF | Hi Max, turn off the radio | | 3 ×2 Tap |
| PREVIOUS STATION | Hi Max, previous station | | 2 3S |
| NEXT STATION | Hi Max, next station | | 1 3S |
| FACTORY RESET | | | 2 + 3 3S |

**Note: The voice command above are for high-end models.**
**For other models, Please refer to the manual for the number of voice command.**

## RF exposure statement

This equipment complies with the FCC and ISED radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.
Cet équipement est conforme aux limites d'exposition aux rayonnements de la FCC et de l'ISED établies pour un environnement non contrôlé. Cet émetteur ne doit pas être co-localisé ou fonctionner en conjonction avec une autre antenne ou un autre émetteur.

## FCC Warning

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
—Reorient or relocate the receiving antenna.
—Increase the separation between the equipment and receiver.
—Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
—Consult the dealer or an experienced radio/TV technician for help.
NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

## IC WARNING

This device contains licence-exempt transmitter(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:
(1) This device may not cause interference.
(2) This device must accept any interference, including interference that may cause undesired operation of the device.
L'émetteur/récepteur exempt de licence contenu dans le présent appareil est conforme aux CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:
1. L'appareil ne doit pas produire de brouillage;
2. L'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.