
SMART LOCK-Key Box User Manual



Type 1 Type 2

V.1: KBb230616E

Basic Information

- Valid Password Length: 6-8 Digits (No Included in Type 1)
- Key Capacity:
100 User Passwords (No Included in Type 1)
50 Fingerprints
- Any fingerprint can unlock the box in factory mode

LED Satus Indication:
- Blue: In Configuration Mode, Low Voltage Reminder
- Green: Correct Operation
- Red: Wrong Operation
- White: Standby Mode

Input Voltage: 4.5V ~ 5.5V
Working Temperature: -20°C~+60°C
Storage Temperature: -20°C~+60°C
Working Humidity: 10% ~ 90%RH
Low Voltage Alarm: ⩽3.6V
Charging Interface: TYPE-C

Tuya Smart Operation Instructions

I . Download and Install

1. Scan the QR code below to download the APP.
(Tips: It can also download "TUYA Smart" from Apple Store/Android Market.)

2. Finished the download, then clicking the operations as below to follow:
"Install from App Gallery" → "Open" → "Agree".

3. Log in via email or phone number, then clicking "getting verification code" to enter.
(Tips: It can selete the country/region as your condition through the system default settings.)

Tuya Smart


II . Bluetooth Pairing Connection

(Note: Keep your phone close to the lock during the process)

1. Open Tuya APP, click the "+" sign in the upper right corner, and select "Add Device".

2. Wake up the smart lock, and click "Add" after the lock appearing on the phone interface.


3. Waiting for the addition to be successful.
After "√" appears, the Bluetooth connection will be well done. Then clicking "Done".



III. App Interface Description & Function Brief Introduction



The operation records that can be viewed in the operation log including:
a. Unlock Records;
b. Unlock Methods;
c. Add/Delete Passwords/Fingerprints;
d. Add/Delete Users;
e. Low battery alert;
f. Modify Unlocking Time Limit, such as user unlocking time limit, temporary password unlocking time limit, etc..



Temporary Code Unlocking Setting:
(Type 2 only)
a. Limited Time Using Temporary Code;
b. One-Time Using Temporary Code;
c. Clear the Temporary Code.

Tips:
1. It can manually set code OR create random code through system.
2. It can set the starting & ending using time of temporary code.
3. It can share temporary code to others via SMS or social media.




Slide left to close the lock.
Slide right to unlock.



Other Function Settings:
a. Enable/Disable Remote Unlocking;
b. Enable/Disable Automatic Unlocking (Recommend to set as Enable);
c. Volume Adjustment
d. DND Mode (Enable/Disable the Alarm from Lock and Phone, Disable as Default);



Membership Management:
a. Add Member Account (Click "+" sign in the upper right corner and choose "ADD MEMBER", then input your member name and member account to save);
b. Enter Member Account to Set Member's Fingerprint/Code




Intelligence Application Scenes:
a. When the family member comes home, it can receive the notification from lock system;
b. If there is abnormal alarm, it can receive the notification from lock system.

Tips:
1. The two scenes can be enabled/disabled.
2. There are 3 types notifications to choose:
① Message Center ② SMS Notification ③ Telephone Notification
3. The realization of the scenes requires the use of smart lock and gateway.

IV. Add Unlock Keys

Please add the unlock method and set the effective time according to the following tips in member management.
(Type 1 can only be added with fingerprint;
Type 2 can be added with fingerprint and password.)



V . Factory Setup

Option 1: Press "RESET" Button

Long press the "RESET" button for 3 seconds, the buzzer beeps "di" for once , the LED flashes in green for once. Then the initialization is successful.




Option 2: Electronic Key

Insert the emergency electronic key into the Type-C port, the key box will be initialized and opened automatically (Please keep it in a safe place)

Option3: Remove Device

After doing the following, the device will be removed from the device list and reset to factory settings. All related data will be wiped.



Note



Follow these steps when locked:

1. Put the shackle through the fixed hole or railing.

2. Turn the lock body so that the lock shackle is aligned with the shackle of the lock body, and press the lock shackle down.

3. Close the lock body.

4. Verify the key or swipe left at the bottom of the APP homepage. At this time, the lock tongue is stretched out and locked successfully.
(Tip: If automatic locking is set in the APP, please ignore the last step)